

Q6504A

HP LaserJet 3050MFP, (Print, Copy, Scan, Fax)

This file was downloaded from [here](#)



Product Description

HP LaserJet 3050MFP, (Print, Copy, Scan, Fax) 18ppm, 64MB Memory, 1200dpi, Sheet Feed, 30 page ADF

Specifications on this product range

System features

Print Speed / Processor / Memory

Print speed (black, normal quality, A4) Up to 18 ppm

Processor type Motorola Coldfire® v 4e

Processor speed 264 MHz

Standard memory 64 MB

Maximum memory 64 MB

Printing System

First page out (black, A4) 8 sec

Pages per month Up to 7,000

Print quality (black, normal quality) Up to 1200 x 1200 dpi

Duplex print options Manual (driver support provided)

Standard Printer HP PCL 6, HP PCL 5e, HP Postscript Level 3 emulation

Languages

Copy System

Maximum copy speed (black, A4) Up to 18 cpm

Maximum number of copies	Up to 99
Copy resolution (black graphics)	Up to 600 x 600 dpi
Copier resize	25 to 400% (1% increments)

Scan System

Scan type	Sheetfed
Enhanced scanning resolution	Up to 19200 dpi
Optical scanning resolution	Up to 600 dpi
Maximum scanning size	216 x 381 mm
Minimum scanning size	74 x 105 mm
Bit depth	24 bit
Color scanning	Yes
Gray scale levels	256
Scan file format	JPEG, TIF, BMP, GIF, PDF, PNG

Fax Functionality

Fax speed (A4)	33.6 Kbps (3 sec per page)
A4 pages held in memory	Up to 110 pages (2 MB)
Colour faxing	No
Auto-Redialing	Yes
Fax delayed sending	Yes
Max Nr. of Broadcasting Locations	119 locations

Paper handling / media

Auto Document Feeder Capacity	Standard, 30 sheets
Standard Paper Trays	1 plus 10-sheet priority tray
Maximum Number of Paper Trays	1 plus 10-sheet priority tray
Media types supported	Paper (bond, colour, glossy, heavy, letterhead, light, plain, preprinted, prepunched, recycled, rough), envelopes, transparencies, labels, cardstock

Standard input capacity	Up to 260
Maximum input capacity (sheets)	Up to 260
Standard output capacity	Up to 100
Maximum output capacity	Up to 100
Standard media sizes	Media input tray and priority slot: A4, A5, B5, C5, C6, DL (ISO), postcard; automatic document feeder (ADF): A4, A5
Custom media sizes	Media input tray and priority slot: 76 x 127 to 216 x 356 mm; automatic document feeder (ADF): 148 x 105 to 216 x 381 mm
recommended media weight	75 to 90 g/m ²
Paper handling	250-sheet input tray, 10-sheet priority tray, 30-sheet automatic document feeder, 100-sheet output bin

Other technical information

Standard connectivity	Hi-Speed USB (compatible with USB 2.0 specifications) port
Optional connectivity	HP Jetdirect External Print Servers: HP Jetdirect en3700, ew2400
Compatible operating systems	Microsoft® Windows® 2000, XP (full solution); 98 SE, Me, XP-64, Server 2003, Linux (print driver only); Mac OS X v 10.3 and higher (full solution)
Compatible network operating systems	Via optional HP Jetdirect External USB Print Servers (print only solution; no support for printer's Embedded Web Server, fax or scan solutions): Microsoft® Windows NT® 4.0, 98, Me, 2000, XP, XP-64, Server 2003; Novell® NetWare NDPS services via TCP/IP only on 3.2, 4.2, 5.x, 6.x; HP Gateway (TCP/IP raw only) and Novell LPD gateway; Mac OS X v 10.3 and later; Bonjour discovery supported; Red Hat Linux 6.x and later; SuSE Linux 6.x and later; HP-UX 10.20, 11.x; Solaris™ 2.5x, 2.6, 7, 8, 9, 10 (SPARC systems only); IBM AIX 3.2.5 and later; MPE-iX; Citrix MetaFrame; Windows Terminal Services
Minimum system requirements	Microsoft® Windows® 98 SE, Me, Server 2003: any Pentium® II processor or greater, 64 MB RAM, 10 MB hard disk space, SVGA 800 x 600 with 16-bit colour display (print driver only); Windows 2000, XP: any Pentium II processor (Pentium III or greater recommended), 128 MB RAM, 250 MB hard disk space, SVGA 800 x 600 with 16-bit colour display, Internet Explorer 5.5 or greater (full install), CD-ROM drive, Hi-Speed USB (compatible with USB 2.0 specifications) port

Control panel	Intuitive control panel with 2-line, 16-character back lit display, alphanumeric buttons, menu and cancel controls, fax, copy and scan controls, speed-dial keys
Software included	HP Toolbox FX, HP LaserJet Scan, TWAIN 1.9 or WIA scan drivers, HP LaserJet Fax, HP Fax Setup Wizard, Readiris PRO text recognition software (not installed with other software, separate installation required), printer drivers (HP PCL 6, HP PCL 5e, HP Postscript Level 3 emulation), installer/uninstaller, HP Director (Macintosh)
Hard disk capacity	None
Power consumption	0 watt (off), 5 watts (powersave and standby), 290 watts (active)
Power requirements	Input voltage 220 to 240 VAC (+/- 10%), 50/60 Hz (+/- 2 Hz), 2.3 amp
Operating temperature range	15 to 32.5° C
Dimensions (W x D x H)	429 x 443 x 459 mm
Weight	9.3 kg
What's in the box	HP LaserJet 3050 All-in-One, HP LaserJet Q2612A Black Print Cartridge, getting started guide, support flyer, CDs containing device software and electronic user's guide, Readiris PRO text recognition software, 250-sheet media input tray, ADF input support, ADF output support, output bin support, power cord(s), phone cord(s), one year limited warranty
Warranty	One-year limited warranty

At a glance

Model	Key features
HP LaserJet 3050 All-in-One (Q6504A)	HP LaserJet 3050 All-in-One: print speed of up to 18 ppm, 1200 dpi print resolution, 600 dpi copy resolution, 64 MB memory, 33.6 Kbps faxing (V.34, Super G3), with two RJ-11 ports, standard input capacity of 250-sheets, 10-sheet priority feed and 30-page automatic document feeder

Accuracy of information is not guaranteed.
Images are a reference and may differ from actual product.
E&OE. [Terms and conditions apply.](#)

Full site: <http://www.comx.co.za/>

Mobile site: <http://m.comx.co.za/>

Enhanced mobile site: <http://touch.comx.co.za/>

Facebook: <http://www.facebook.com/pages/ComX-Computers/130126582879>

Twitter: <http://twitter.com/comxcomputers>

